

RIBMNA1D0



Functional
Devices, Inc.

B1087 • 393096A

Input Voltage

24Vac/dc

Input Current

90mA Max

Feedback Contact

2A Max @ 24Vac/dc


Override Impedance Limitations

0-5Vdc, 200 Ω Min

0-10Vdc, 400 Ω Min

0-15Vdc, 1k Ω Min

0-20mAdc, 500 Ω Max



Legend for Selecting Output for Jumpers

- Top 2 pins covered by jumper
- Bottom 2 pins covered by jumper
- Only 1 pin covered by jumper



Notes:

- » Set the jumpers according to your input signal (Analog signal from the controller.) Example: When controlling a damper with 0-10 Vdc, the jumpers need to be in position for the 0-10 Vdc override range. If the LED range does not match your analog scale, ensure the jumpers are set for the proper range.
- » Feedback contact closed when switch is in Manual position, open when switch is in Auto position.